



Original Bushing Information

Original Bushing Manufacturer: G.E. **Mounting Position:**
Catalog Number: 11B153BB
Voltage Class (kV): 138 **BIL (kV):** 650

Application	DrawLead	Bottom Connected	Oil Circuit Breaker
Current Rating (Amps)	800		
138W0800XG (Amps)	800		

General Comments:

Replacement Information

ABB Style Number: [138W0800XG](#) **Alternate ABB Style Number:**

Review dimensional differences verifying critical dimensions to meet application requirements.

Notes/Comments:

Catalog Number	BIL	EL	CT	L	B	D	Bolt Circle	No. Of Holes	Hole Dia. (inches)	Creep
11B153BB	650kV	23 in.	23 in.	47.19 in.	74.19 in.	9.75 in.	14.25 in.	6	1.25 slots in.	141.5 in.
138W0800XG	650kV	23 in.	23 in.	47.172 in.	74.281 in.	9.75 in.	14.25 in.	6	1.25 in.	143.25 in.

Catalog Number	Strike	P Dia.	Cable Height/Pin Height for AB Bushing - CH	LHV	Top Terminal Threads (inches)	Bottom Terminal Thread/Configuration
11B153BB	56.75 in.	10.63 in.	64.07 in.	62.75 in.	1.5-12 x 2.0	ansi/IEEE fig 2
138W0800XG	56.765 in.	9.500 in.	64.202 in.	62.765 in.	1.500-12UN-2A, 2.250 USABLE THD, SP x	1.625 i.d. tube N/A

Cable Adapter: NONE
Flange Adapter: NONE