



Original Bushing Information

Original Bushing Manufacturer: G.E. **Mounting Position:**
Catalog Number: 11B331BB
Voltage Class (kV): 138 **BIL (kV):** 650

Application	DrawLead	Bottom Connected	Oil Circuit Breaker
Current Rating (Amps)		3000	
138W3000UA (Amps)		3000	

General Comments:

Replacement Information

ABB Style Number: [138W3000UA](#) **Alternate ABB Style Number:**

Review dimensional differences verifying critical dimensions to meet application requirements.

Notes/Comments:

Catalog Number	BIL	EL	CT	L	B	D	Bolt Circle	No. Of Holes	Hole Dia. (inches)	Creep
11B331BB	650kV	23 in.	23 in.	46.75 in.	56.06 in.	9.75 in.	14.25 in.	6	1.25 slots in.	99.8 in.
138W3000UA	650kV	23 in.	23 in.	46.734 in.	56.11 in.	9.75 in.	14.25 in.	6	1.25 in.	104.188 in.

Catalog Number	Strike	P Dia.	Cable Height/Pin Height for AB Bushing - CH	LHV	Top Terminal Threads (inches)	Bottom Terminal Thread/Configuration
11B331BB	42.12 in.	9.63 in.	N/A	48.124 in.	3.0"-12X3.0" THDS	ansi/IEEE fig 2 or 3
138W3000UA	42.141 in.	9.500 in.	N/A	48.141 in.	3.0-12x3.500 USABLE, SP x	IEEE fig 2 & 3 N/A

Cable Adapter:

NONE

Flange Adapter:

NONE